MA3 Microphone Amplifier

Hardware Reference

Updated 2024-02-05

© 2016-2024 Tucker-Davis Technologies, Inc. (TDT). All rights reserved.

Tucker-Davis Technologies
11930 Research Circle
Alachua, FL 32615 USA
Phone: +1.386.462.9622
Fax: +1.386.462.5365

Notices

The information contained in this document is provided "as is," and is subject to being changed, without notice. TDT shall not be liable for errors or damages in connection with the furnishing, use, or performance of this document or of any information contained herein.

The latest versions of TDT documents are always online at https://www.tdt.com/docs/

Table of Contents

MA3 Microphone Amplifier

MA3 Overview 4

Power 4

MA3 Features 4

Inputs 4

Bias 5

Gain Control 5

Outputs 5

MA3 Technical Specification 5

MA3 Output 6

MA3 Frequency Response 6

MA3 Microphone Amplifier

MA3 Overview

The MA3 is a two-channel microphone amplifier for auditory scientists. This high-quality low-cost system is designed for use with both ¼" audio jack microphones and balanced XLR inputs for optimum impedance and noise characteristics. The MA3 can provide a bias voltage for microphones that require it. Two BNC connectors provide analog output. A variable gain knob provides amplification from 10 dB to 55 dB in 5 dB steps. A toggle switch provides 20 dB of additional gain for over 5000x total amplification.

Power

The MA3 Microphone Amplifier is powered via the System 3 zBus (ZB1PS). No PC interface is required.

MA3 Features

Inputs

The MA3 comes with three inputs: an XLR microphone input and two ¼" TRS connector inputs. Signals from two microphones can be amplified simultaneously.

Bias

The Bias switch produces a bias voltage for microphones that require it.

Gain Control

The gain control amplifies the microphone input in 5 dB steps from 10-55 dB (~3x - ~560x). The Gain Switch adds an additional 20 dB (10x) of gain for a maximum amplification of ~5600x.

Outputs

Two BNC outputs give easy connection to any TDT System 3 device. The maximum voltage output is ±10 Volts. Clip lights indicate and overvoltage on the signal output.

MA3 Technical Specification

Input Signal Range	±10 V peak
-3 dB Bandwidth	200 kHz @ 40 dB gain
Gain Accuracy	±1 dB
Spectral Variation	1 dB from 20 Hz to 20 kHz
Signal/Noise	110 dB (20 Hz to 30 kHz at 9.9 V)
Noise Floor	9.2 uVrms
THD	<0.002% (1 kHz tone, ±7 V peak)
Input Impedance	600 Ohm
Output Signal Range	±10 V peak
Bias Voltage	10 V, 150 mA max, superimposed onto microphone
Output Impedance	5 Ohm

MA3 Output



MA3 Frequency Response